



Switch, S1, in extreme counter clockwise position (POS. 1)

SELECTOR SWITCH POSITIONS

- Pos. 1 10 mmfd-5000 mmfd
- Pos. 2 .001 mfd-.5 mfd
- Pos. 3 .1 mfd-50 mfd
- Pos. 4 50 mfd-5000 mfd
- Pos. 5 .5 Ω - 500 Ω
- Pos. 6 50 Ω - 50KΩ
- Pos. 7 5KΩ - 5MΩ
- Pos. 8 5MΩ - 500MΩ
- Pos. 9 Comparator
- Pos. 10 Paper-Mica Test
- Pos. 11 Electrolytic Test

Sym.	Description	Sym.	Description	Sym.	Description
C1	cap., elec 8mfd-525V	P3	pot., 100KΩ, 4W	R9	res., 270KΩ, 1/2 W
C2	cap., 200mmf, prec.	R1	res., 500Ω, 4 W	R10	res., 10MΩ, 1/2 W
C3	cap., .02 mf, prec.	R2	res., 250K, 1/2 W, 1%	R11	res., 2.2KΩ, 1W
C4	cap., 2 mf, prec.	R3	res., 1MΩ, 1/2 W	R12	res., 470K, 1/2 W
C5,6,7	cap., .01 mf-400V	R4	res., 20Ω, 1/2 W, 1%	S1	switch, range
C8	cap., .25 mf-600V	R5	res., 2KΩ, 1/2 W, 1%	S2	switch, SPST, p/o P2
C9	cap., elec 4 mfd-250V	R6	res., 200KΩ, 1/2W,1%	V1	tube, 6X5
P1	pot., 10KΩ	R7	res., 3.3KΩ, 1W	V2	tube, 1629
P2	pot., 1KΩ w/SPST	R8	res., 68KΩ, 1W		

MODEL 950B RESISTANCE-CAPACITANCE-COMPARATOR BRIDGE